

Date:	_____
Project:	_____
Price:	_____

# EM Backup For 4" & 6" LED Flat Retrofit Kits


## Description:

Our energy efficient LED Flat Retrofit kit provides quick and easy installation with no can required. This fixture can be equipped with our featured 180-320VDC (or 120-230VAC) emergency backup. Can be used with switched or unswitched fixtures. Compatible with LED lamp loads of up to 20W.



## Features:

- Universal 120-277V, 50/60 Hz input
- Charge/Power "ON" LED indicator light and push-to-test switch for mandated code compliance testing
- Long-life, maintenance free, rechargeable NiCad battery.
- Output short/overcurrent protection: Electronic limiting, with normal operation resuming upon removal of fault 90 Minute minimum emergency operating time over full temperature range
- 24 Hour maximum battery recharge time
- LED illuminated and remote mounted test switch
- Durable painted steel construction in red/orange finish
- Provided with 18" flex conduits on both ends
- Suitable for installation inside or top of the fixture
- UL Recognized for factory installation
- Suitable for damp locations (0°C - 55°C)
- 7-Year Warranty on all electronics and housing.
- Meets UL924, NFPA 101 Life Safety Code, NEC, OSHA, & Local and State codes



Push-to-Test Indicator Included

## DIMENSIONS

